

Royal® Model

Sensor Operated Flushometers



Description

Concealed, Sensor Operated Royal® Model Water Closet Flushometer, enclosed behind a 13" x 17" Wall Box with Stainless Steel Access Panel, for wall hung back spud bowls.

Flush Cycle

Model 152 WB ES-S Water Saver (3.5 gpf/13.2 Lpf) Model 152-1.6 WB ES-S Low Consumption (1.6 gpf/6.0 Lpf)

Specifications

Quiet, Concealed, Diaphragm Type, Rough Brass Closet Flushometer with the following features:

- PERMEX™ Synthetic Rubber Diaphragm with Dual Filtered Fixed Bypass
- OPTIMA[®] EL-1500-L Self-Adaptive Infrared Sensor with Indicator Light
- User friendly three (3) second Flush Delay
- Courtesy Flush™ Override Button
 Non-Hold-Open Integral Solenoid Operator
- 13" x 17" EASY ACCESS® Wall Box with Stainless Steel Access Panel and Vandal Resistant Screws
- 1" I.P.S. Wheel Handle Bak-Chek™ Angle Stop
- Adjustable Tailpiece
- · High Back Pressure Vacuum Breaker Flush Connection and Spud Coupling for 11/2" Concealed Back Spud
- Sweat Solder Adapter
- High Copper, Low Zinc Brass Castings for Dezincification Resistance
- Non-Hold-Open Integral Solenoid Operator, Fixed Metering Bypass and No External Volume Adjustment to Ensure Water Conservation
- Flush Accuracy Controlled by CID[™] Technology
- Diaphragm, Stop Seat and Vacuum Breaker to be molded from PERMEX[™] Rubber Compound for Chloramine Resistance

Valve Body, Cover, Tailpiece and Control Stop shall be in conformance with ASTM Alloy Classification for Semi-Red Brass. Valve shall be in compliance with the applicable sections of ASSE 1037, ANSI/ASME A112.19.6 and Military Specification V-29193. Installation conforms to ADA requirements.

L Dimension

Specify the "L" Dimension for the proper length of the Flush Connection. The "L" Dimension is equal to the Wall Thickness (to nearest whole inch) plus 23/4".

Variations

Trap Primer Elbow

Accessories

□ EL-154 Transformer (120 VAC/24 VAC, 50 VA) Transformer (240 VAC/24 VAC, 50 VA) □ EL-342

See Accessories Section and OPTIMA Accessories Section of the Sloan catalog for details on these and other OPTIMA Flushometer variations.

U R Listed	()	$^{\mathbb{R}}$ Certified	UPC ® L	isted by I.A.P.M.O.	F
This space for Architect/Engineer approval					
Job Name				Date	
Model Specified				_ Quantity	
Variations Specified					
Customer/Wholesaler _					
Contractor					
Architect					



Automatic

Sloan OPTIMA® equipped Flushometers provide the ultimate in sanitary protection and automatic operation. There are no handles to trip or buttons to push. The Flushometer operates by means of an infrared sensor that adapts to its surrounding. Once the user enters the sensor's effective range and then steps away, the Flushometer Solenoid initiates the flushing cycle to flush the fixture. Wall Box allows for vandal-proof concealed installation where pipe chase is not available or pipe space is limited.

Hygienic

User makes no physical contact with the Flushometer surface except to initiate the Override Button when required. Helps control the spread of infectious diseases. Twenty-four Hour Sentinel Flush keeps fixture fresh during periods of nonuse.

Economical

Automatic operation provides water usage savings over other flushing devices. Reduces maintenance and operation costs.

Practical

Solid state electronic circuitry assures years of dependable, trouble-free operation. The operational components of the Flushometer are identical to a handle operated Royal® Flushometer, proven by 90 years of experience.

Warrantv

3 year (limited)

Made in the U.S.A.



Description

Concealed, Sensor Operated Royal® Model Water Closet Flushometer, enclosed behind a 13" x 17" Wall Box with Stainless Steel Access Panel, for wall hung back spud bowls.

Flush Cycle

□ Model 152 WB ES-S Water Saver (3.5 gpf/13.2 Lpf) □ Model 152-1.6 WB ES-S Low Consumption (1.6 gpf/6.0 Lpf)

ELECTRICAL SPECIFICATIONS

Control Circuit

- Solid State 24 VAC Input 24 VAC Output 8 Second Arming Delay 3 Second Flush Delay 24 Hour Sentinel Flush
- OPTIMA Sensor Range

Nominal 22" - 42" (559 mm - 1067 mm) Self-adaptive Window \pm 10" (254 mm)

4"

(102 mm)

6

6" (152 mm)

MIN. SPACE

IN WALL

"L " Dim. 23/4" (70 mm)

+ WALL THICKNESS

t

REQUIREMENT

- OPERATION
- A continuous, invisible light beam is emitted from the OPTIMA Sensor.



41/4" (108 mm)

Ŧ

141/2"

(368 mm)

8" (203 mm)

OF FIXTURE

TO TOP

171/8"

(435 mm)

- Solenoid Operator 24 VAC, 50/60 Hz
 - Wall Box Specifications EASY ACCESS* Wall Box Assembly — Part #EL-192-A Frame: 13" x 17" x 4" (330 mm x 432 mm x 102 mm) #16 Gauge Steel Cover (Access Panel): 14½" x 18½" (368 mm x 470 mm) #15 Gauge #304 Stainless Steel, #4 Finish Screws: (6) #8-32 x ¾" Drilled Spanner Head — Spanner Bit Provided
 - 2. As the user enters the beam's effective range (22" to 42") the beam is reflected into the OPTIMA Scanner Window and transformed into a low voltage electrical circuit. Once activated, the Output Circuit continues in a "hold" mode for as long as the user remains within the effective range of the Sensor.

OVERRIDE

OPTIMA

SENSOR

븅

43/4" (121 mm)

131/8" (333 mm)**†**

141/2" (368 mm)

C/L

OF FIXTURE

BUTTON

71/4

(184 mm)

1" I.P.S.


WATER

SUPPLY

181/2

(470 mm)

(25 mm DN)



WIRING

DIAGRAM

EL-1500-L SENSOR

EL-1500-L SENSOR

Transformer

Sloan Part #EL-154

Sloan Part #EL-342

120 VAC, 50/60 Hz Primary

Class II, UL Listed, 50 VA.

240 VAC, 50/60 Hz Primary

Class II, UL Listed, 50 VA.

24 VAC, 50/60 Hz Secondary

24 VAC. 50/60 Hz Secondary

120 VAC

24 VAC

COIL WIRE

COIL WIRE

OVERRIDE BUTTON

 Π

 Π

OVERRIDE BUTTON

24 VAC COIL

SOLENOID GROUND

24 VAC COIL

SOLENOID


GROUND

WIRE

WIRE


····

3. When the user steps away from the OPTIMA Sensor, the circuit waits 3 seconds (to prevent false flushing) then initiates an electrical "onetime" signal that operates the Solenoid. This initiates the flushing cycle to flush the fixture. The Circuit then automatically resets and is ready for the next user.



ELECTRICAL BOX INSTALLATION SENSOR LOCATION AND POSITIONING IS CRITICAL

Failure to properly position the electrical boxes to the plumbing rough-in will result in improper installation and impair product performance. All tradesmen (plumbers, electricians, tile setters, etc.) involved with the installation of this product must coordinate their work to assure proper product installation.



Adjust the Mounting Bracket so that the Sensor sits flush against the Cover Plate.

Refer to the instructions packaged with the Flushometer for additional installation information.

SLOAN VALVE COMPANY • 10500 SEYMOUR AVENUE • FRANKLIN PARK, IL 60131

Phone: 1-800-9-VALVE-9 or 1-847-671-4300 • Fax: 1-800-447-8329 or 1-847-671-4380 • http://www.sloanvalve.com

Copyright © 2002 Sloan Valve Company

REQUIRED WALL OPENING

Printed in the U.S.A.

Made in the U.S.A.

Royal Optima 152 WB ES-S S.S. - Rev. 1 (01/02)

One Transformer serves up to ten (10) OPTIMA Closet/Urinal Flushometers. Specify number of transformers required accordingly.

GND

ΠΠ

UNIT #1

UNIT #2

THRU #10

(IF USED)