

SoundTile<sup>®</sup>

Speaker (Pair) K-8033

#### **Features**

- Low profile design.
- Compliments the WaterTile product line.
- Can be used with any audio system and also integrated with the DTV+™ Digital Showering System.

#### Installation

- Mounts within a standard 2x4 wall.
- Mounts to the wall or ceiling.
- Speaker installs after finished wall is complete.

### **Optional Products/Accessories**

K-99696 Amplifier Module

Loose component/s: Female quick disconnect terminals, Speaker mounting screws, and Speaker cover.



#### Codes/Standards

UL 1480

# KOHLER® Electronic Faucets, Valves, and Controls Five-Year Limited Warranty

See website for detailed warranty information.

#### **Available Colors/Finishes**

Color tiles intended for reference only.

Color	Code	Description
	CP	Polished Chrome
	SN	Vibrant® Polished Nickel
	AF	Vibrant® French Gold
	BN	Vibrant® Brushed Nickel
	BV	Vibrant® Brushed Bronze
	2BZ	Oil-Rubbed Bronze
	BL	Matte Black
	TT	Titanium
	VNT	Vintage Nickel





# **KOHLER**, Faucets

## **SoundTile®**


Speaker (Pair)


K-8033





**Cutout Detail** 





#### **Technical Information**

All product dimensions are nominal.

Speaker wire gauge: Accepts 12-16 AWG

Max. Ambient temp: 122°F (50°C)
Peak power: 135 Watts
Average power: 45 Watts

#### **Notes**

Install this product according to the installation guide.

Recommended wire connections using solder or standard quick-disconnect terminals (0.187"  $\times$  0.020" for the positive connection and 0.110"  $\times$  0.020" for the negative connection).

Installer to provide sheathed speaker wire.