


FlameGuard® Technical  
**FlameGuard® Product Weights & Dimensions**



### Reducing Cross


Socket x Socket x Socket x Socket



Part Number	Size	G	G1	H	H1	L	L1	M	M1	Approx. Wt. (Lbs.)
4220-131	1X3/4	23/32	5/8	1- 5/8	1- 5/8	3- 1/4	3- 1/4	1- 7/8	1- 1/2	.35
4220-167	1-1/4X3/4	3/4	1-1/32	2	2- 3/64	4	4- 3/32	2- 1/16	1-3/8	.35
4220-210	1-1/2X3/4	11/16	1- 5/32	2- 3/32	2-11/64	4- 3/16	4-11/32	2- 3/8	1-13/32	.41
4220-248	2X3/4	11/16	1-7/16	2-13/64	2-7/16	4-13/32	4-7/8	2-29/32	1-13/32	.55
4220-289	2-1/2X1	29/32	1- 3/4	2-43/64	2- 7/8	5-11/32	5- 3/4	3- 1/2	1- 3/4	.98

### Coupling


Socket x Socket



Part Number	Size	L	M	N	Approx. Wt. (Lbs.)
4229-007	3/4	1-31/32	1-5/16	3/32	.04
4229-010	1	2- 3/16	1- 5/8	3/32	.07
4229-012	1-1/4	2-19/32	2	3/32	.12
4229-015	1-1/2	2- 7/8	2-11/32	3/32	.22
4229-020	2	3- 1/8	2-27/32	3/32	.32
4229-025	2-1/2	3-11/16	3-15/32	3/16	.58
4229-030	3	4	4- 3/16	3/16	.85

### Reducer Coupling

Socket x Socket



Part Number	Size	L	M	M1	N	Approx. Wt. (Lbs.)
4229-131	1X3/4	2- 3/8	1-23/32	1-13/32	7/32	.11
4229-167	1-1/4X3/4	2-19/32	2- 3/32	1- 5/8	11/32	.14
4229-168	1-1/4X1	2-11/16	2- 3/32	1-23/32	5/16	.17
4229-210	1-1/2X3/4	2-13/16	2-11/32	1-13/32	15/32	.18
4229-211	1-1/2X1	2- 7/8	2-13/32	1-15/16	3/8	.21
4229-212	1-1/2X1-1/4	2-13/16	2-13/32	2- 1/8	5/32	.22