

GT500W

Gotcha Sensor with 110° view, surge protection, 500 watt switching capacity, auto test logic and manual override.

Color: White

Weight: 0.8 lbs



Technical Specifications

UL Listing:

Suitable for wet locations.

Voltage:

120 volts AC 60 Hz.

Power Consumption:

1 watt

Time Adjustment:

10 seconds to 5 minutes

Surge Protection:

Withstands up to 6000 volts

Photoelectric Control:

Deactivates lights during daylight

Detector Sensitivity:

Adjustable from 100% to 50%

Wall Switch Manual Override:

Two flip logic prevents activation by momentary power outages. Override resets to auto after 6 hours or at dawn. No extra wiring needed.

Sensor Housing:

Made of tough, corrosion resistant polycarbonate

Floodlights:

Made of tough, corrosion-resistant polycarbonate. For extra or replacement floodlights, order cat# TUFFY in your choice of color. Accepts PAR-38 lamps, medium base, 150 watts max. Lamps not included.

Detection:

110° view

Switching Capacity:

500 watts Incandescent @120 volts, 5 amps 250 watts Fluorescent

Patents:

RAB sensor and fixture designs are protected under U.S. and International Intellectual Property laws

